



RELOAD – default configuration IP: 192.168.0.7
 name: admin
 password: admin

Process: 1/ disconnect power supply
 2/ set jumper Reload
 3/ connect power supply and wait 10s
 4/ !!! disconnect jumper Reload !!!



CONDITIONS OF WARRANTY

ComErgon provides full warranty of 24 month for serial interface module PRO 4.0/232 starting on the day of purchase. The warranty is except for the cases in which the functioning of the module has been affected by faulty manipulation, natural catastrophes or other external factors.

Note: Default port: 23
 Valid range 1025-9998, 10000-13999, 14010-30703 a 30719-65535

PRO 4.0/232 K3
 converter
RS 232 - Ethernet

ethernet module protocol	K3 USR TCP, IP, UDP, ARP, ICMP, DNS, DHCP HTTP, Web socket, HTTPD client, MODBUS 10/100 Mb/s, MDI/MDIX, auto switch
network interface	RS 232 - full duplex
serialport	RS 232 - full duplex
data bits	5, 6, 7, 8
stop bits	1, 2
parity	None, Even, Odd, Space, Mark
flow control RS232	RTS/CTS, none
transfer rate	600b/s – 512kb/s
transferred signals setting	RxD, TxD internal web server, PC built-in SW, serial command
optical indication	RxD, TxD, Link activity, PWR
connector RS232	D-SUB 9 pin M
connector Ethernet	RJ45
connector supply	plug 1.3mm
supply	5 - 32V DC
input supply	max 2W
dimension	95 x 57 x 28 mm